

CAT CX35-P800 Oilfield Transmission

<https://www.zepelin-powersystems.com/de/en/>



| | |
|-------------------------|----------------|
| Gross Input Power | 597 kW |
| Gross Peak Input Torque | 2.700 N·m |
| Rated Input Speed | 2.100 r/min |
| Maximum Turbine Torque | 2.700 N·m |
| Minimum Input Speed | 600 r/min |
| Electrical System | 12 V |
| Gear Type | Planetary Spur |
| Gears | 8F/1R |
| 1F Gear Ratio | 5,73 |
| 2F Gear Ratio | 3,57 |
| 3F Gear Ratio | 2,72 |
| 4F Gear Ratio | 1,95 |
| 5F Gear Ratio | 1,43 |
| 6F Gear Ratio | 1 |
| 7F Gear Ratio | 0,74 |
| 8F Gear Ratio | 0,63 |
| 1R Gear Ratio | -4,46 |
| Overall Gear Ration | 9,1 |

This offer is without obligation. The offer is based on our General Terms and Conditions of Sale and Delivery. Changes to equipment and accessories required for technical reasons may be made at any time. Subject to errors, changes and intermediate sale. Statutory value-added tax shall be added to all price.