

CAT G3306B Oilfield Gas Generator Set

<https://www.zeppelin-powersystems.com/de/en/>



Maximum Rating	135 ekW (170 kVA)
Minimum Rating	110 ekW (138 kVA)
Emissions/Fuel Strategy	NSPS or non-regulated
Aspiration	Turbocharged-Aftercooled
Manifold Type	Watercooled
Bore	121 mm
Stroke	152 mm
Displacement	10,5 l
Engine Control and Protection	ADEM A4
Generator Set Control	EMCP 4.3 (4.4 optional)
Generator	SR4B
Frequency - Speed	50/60 Hz (1500/1800 rpm)
Fuel	CNG, LNG, field gas, natural gas
Lube Oil System - Refill	44,5 l
Cooling System - Engine	20 l
Length	3.704 mm
Width	1.530 mm
Height	1.856 mm
Weight	3.500 ton (US)
Minimum Rating	138 kVA
Maximum Rating	170 kVA
Rated Speed	1500/1800 rpm

This offer is without obligation. The offer is based on our General Terms and Conditions of Sale and Delivery. Changes to equipment and accessories required for technical reasons may be made at any time. Subject to errors, changes and intermediate sale. Statutory value-added tax shall be added to all price.